

Listing of Claims:

Sub G'7
Claims 1 - 222 (previously canceled)

Claim 223 (once previously amended, currently amended)

A voltage reference circuit responsive to an external voltage for supplying a reference voltage, comprising

an active reference circuit for receiving the external voltage and for producing a reference signal having a desired relationship with the external voltage, said active reference circuit comprising a current source utilizing a current mirror for providing current to a diode stack having an adjustable impedance, wherein said reference signal is dependent upon said external voltage; and

a unity gain amplifier responsive to said reference signal for producing the reference voltage. **G**

Claim 224 (previously canceled)

Claim 225 (once previously amended)

The voltage reference circuit of claim 223 wherein said diode stack includes a plurality of transistors connected in series, with each transistor's gate connected to a common potential, and a plurality of switches each for selectively shunting one of said transistors.

Claim 226 (original)

The voltage reference circuit of claim 225 wherein said switches are controlled by fuses, and wherein opening certain of said fuses turns its associated switch on, and wherein opening certain other of said fuses turns its associated switch off.

Claim 227 (original)

The voltage reference circuit of claim 226 wherein said plurality of transistors includes a first plurality of field effect transistors and wherein said plurality of switches includes a second plurality of field effect transistors.

SUB
G17

Claim 228 (original)

The voltage reference circuit of claim 223 additionally comprising a pullup stage for pulling up the reference voltage so as to substantially track the external voltage when the external voltage exceeds a predetermined value.

Claim 229 (original)

The voltage reference circuit of claim 228 wherein said pullup stage includes a plurality of diodes connected between the external voltage and the reference voltage.

Claim 230 (original)

The voltage reference circuit of claim 229 wherein the reference voltage is the external voltage less a voltage drop across said plurality of diodes.

Cmt
F1

Claim 231 (currently amended)

A voltage reference circuit in combination with a power amplifier, said combination comprising:

an active reference circuit for receiving the external voltage and for producing a reference signal having a desired relationship to the external voltage, wherein said reference signal is dependent upon said external voltage;

a unity gain amplifier responsive to said reference signal for producing a reference voltage; and

a power amplifier stage for amplifying the reference voltage by a factor greater than unity to provide an output voltage.

Claim 232 (original)

The combination of claim 231 additionally comprising a circuit for supplying the external voltage as the output voltage when the external voltage is below a first predetermined value.

Claim 233 (original)

The combination of claim 232 wherein said circuit for supplying includes a switch for shorting a bus carrying the external voltage with a bus carrying the output voltage.

SUB
G17

Claim 234 (original)

The combination of claim 232 additionally comprising a pullup stage for pulling up the reference voltage so as to substantially track the external voltage when the external voltage exceeds a second predetermined value.

Claim 235 (original)

The combination of claim 234 wherein said pullup stage includes a plurality of diodes connected between the external voltage and the reference voltage.

Claim 236 (original)

The combination of claim 235 wherein the reference voltage is the external voltage less a voltage drop across said plurality of diodes.

Cmt
F1

Claim 237 (original)

The combination of claim 234 wherein said combination supplies an output voltage which increases at a first slope substantially the same as a slope of the external voltage during a powerup range, increases at a second slope substantially less than a slope of the external voltage during an operating range, and increases at a third slope greater than a slope of the external voltage during a burn-in range of the external voltage.

Claim 238 - 246 (previously canceled)

Claim 247 (currently amended)

A method of supplying an output voltage in response to an external voltage, and wherein the output voltage has a first characteristic when the external voltage is in a powerup range, has a second characteristic when the external voltage is in an operating range, and has a third characteristic when the external voltage is in a burn-in range, said method comprising the steps of:

supplying the external voltage as the output voltage when the external voltage is below a first predetermined value defining the powerup range;

producing a reference signal having a desired relationship with the external voltage,
wherein said reference signal is dependent upon said external voltage;

SUB
G1 7

amplifying the reference signal with a unity gain amplifier for producing a reference voltage when the external voltage is above said first predetermined value;
amplifying the reference voltage by a factor greater than unity to provide the output voltage when the external voltage is not being supplied as the output voltage; and
pulling up the reference voltage so as to substantially track the external voltage when the external voltage exceeds said second predetermined value defining the burn-in range.

Claim 248 (original)

Cmt
F1

The method of claim 247 wherein said step of producing a reference signal includes the steps of generating a current related to the external voltage, applying the current to a circuit node, and draining the current from the circuit node through an adjustable impedance.

Claim 249 (original)

The method of claim 248 additionally comprising the step of adjusting the impedance to modify the reference signal.

Claim 250 (original)

The method of claim 249 wherein said step of adjusting the impedance includes the step of opening a fuse.

Claim 251 - 465 (previously canceled)

Claims 466 - 495 (previously added, previously canceled)

Claim 496 (previously added, once previously amended, currently amended)

A voltage reference circuit responsive to an external voltage for supplying a reference voltage, comprising:

a constant current source for supplying a current to a node in response to the external voltage;

a circuit having an adjustable impedance for draining current from the node, wherein said circuit comprises a diode stack comprised of a plurality of transistors connected in series and a plurality of switches each switch for selectively shunting one of said transistors, and wherein each switch is responsive to a control signal; and

Sub G1 7
a unity gain amplifier responsive to a signal available at the node for producing the reference voltage, wherein said signal is dependent upon said external voltage.

Claims 497-498 (previously added, previously canceled)

Claim 499 (previously added, once previously amended)

The voltage reference circuit of claim 496 wherein said switches are controlled by fuses.

Claim 500 (previously added)

The voltage reference circuit of claim 499 wherein said plurality of transistors includes a first plurality of field effect transistors and wherein said plurality of switches includes a second plurality of field effect transistors.

Claim 501 (previously added)

Cont FI
The voltage reference circuit of claim 496 additionally comprising a pullup stage for pulling up the reference voltage so as to substantially track the external voltage when the external voltage exceeds a predetermined value.

Claim 502 (previously added)

The voltage reference circuit of claim 501 wherein said pullup stage includes a plurality of diodes connected between the external voltage and the reference voltage.

Claim 503 (previously added)

The voltage reference circuit of claim 502 wherein the reference voltage is the external voltage less a voltage drop across said plurality of diodes.

Claim 504 (previously added, currently amended)

A voltage reference circuit in combination with a power amplifier, said combination comprising:

a constant current source for supplying a current to a node in response to an external voltage;

a circuit having an adjustable impedance for draining current from the node;

a unity gain amplifier responsive to a signal available at the node for producing a reference voltage, wherein said signal is dependent upon said external voltage; and

SUB
G' 7

a power amplifier stage for amplifying the reference voltage by a factor greater than unity to provide an output voltage.

Claim 505 (previously added)

The combination of claim 504 additionally comprising a circuit for supplying the external voltage as the output voltage when the external voltage is below a first predetermined value.

Claim 506 (previously added)

The combination of claim 505 wherein said circuit for supplying includes a switch for shorting a bus carrying the external voltage with a bus carrying the output voltage.

Cont
F1

Claim 507 (previously added)

The combination of claim 505 additionally comprising a pullup stage for pulling up the reference voltage so as to substantially track the external voltage when the external voltage exceeds a second predetermined value.

Claim 508 (previously added)

The combination of claim 507 wherein said pullup stage includes a plurality of diodes connected between the external voltage and the reference voltage.

Claim 509 (previously added)

The combination of claim 508 wherein the reference voltage is the external voltage less a voltage drop across said plurality of diodes.

Claim 510 (previously added)

The combination of claim 507 wherein said combination supplies an output voltage which increases at a first slope substantially the same as a slope of the external voltage during a powerup range, increases at a second slope substantially less than a slope of the external voltage during an operating range, and increases at a third slope greater than a slope of the external voltage during a burn-in range of the external voltage.

Claim 511 (newly added)

The voltage reference circuit of claim 223 wherein said reference signal is dependent upon said external voltage within a predetermined testing margin of error.

SUB
G17

Claim 512 (newly added)

The voltage reference circuit of claim 231 wherein said reference signal is dependent upon said external voltage within a predetermined testing margin of error.

Claim 513 (newly added)

The voltage reference circuit of claim 247 wherein said reference signal is dependent upon said external voltage within a predetermined testing margin of error.

Claim 514 (newly added)

The voltage reference circuit of claim 496 wherein said reference signal is dependent upon said external voltage within a predetermined testing margin of error.

Claim 515 (newly added)

The voltage reference circuit of claim 504 wherein said reference signal is dependent upon said external voltage within a predetermined testing margin of error.

Cont
F1